

## Smart Switch Comparison

		MixSwitch				MixSwitch Defy Series		MixSwitch Bach Series	
		MixSwitch 1/2/3 Gang (L&N)	MixSwitch 4 Gang (L&N)	MixSwitch 1/2/3 Gang (Single L)	MixSwitch Control Panel	MixSwitch Defy 3 keys	MixSwitch Defy 4 keys	MixSwitch - Bach 4 keys	MixSwitch - Bach 8 keys
<b>Product</b>	Picture								
<b>Hardware</b>	Color	Grey/White/Golden	Grey/White/Golden	Grey/White/Golden	Grey/White/Golden	Grey/Orange	Grey/Orange	Grey/Blue/Silver/Golden	Grey/Blue/Silver/Golden
	Size	86*86*39mm	86*86*33mm	86*86*39mm	86*86*10mm	92.5 x 86 x 35.25 mm	92.5 x 86 x 35.25 mm	86 x 86 x 38.3 mm	86 x 86 x 38.3 mm
	Cassette Size	86 standard	86 standard	86 standard	86 standard	86 standard	86 standard	86 standard	86 standard
	Screen	N	N	N	N	0.53" IPS Screen x 1	0.53" IPS Screen x 2	N	N
	Power Supply	AC110-250V, 50/60Hz	AC110-250V, 50/60Hz	AC220-250V, 50/60Hz	DC3V (CR2032 battery.)	AC100-240V, 50/60Hz	AC100-240V, 50/60Hz	AC100-240V, 50/60Hz	AC100-240V, 50/60Hz
	Control Method	APP, Button	APP, Button	APP, Button	APP, Button	APP, Button	APP, Button	APP, Button	APP, Button
	Communication Protocol	zigbee	zigbee	zigbee	zigbee	zigbee	zigbee	zigbee	zigbee
	Built-in Light Control	1/2/3	4	1/2/3	N	3	4	4	4
	Maximum Load	400W/gang (Old version: 200W/gang)	400W/gang	200W/gang	-	400W/gang	400W/gang (Totally four loops should less than 1200W)	800W/gang (Totally four loops should less than 1200W)	800W/gang (Totally four loops should less than 1200W)
Button	1/2/3	6	1/2/3	6	3	4	4	8	
<b>Feature</b>	Lighting Control	Y	Y	Y	Y	Y	Y	Y	Y
	Scene Control	Y	Y	Y	Y	Y	Y	Y	Y
	Signal Repeater	Y	Y	N	N	Y	Y	Y	Y
	Power Memory	Y	Y	Y	-	Y	Y	Y	Y
	Proximity sensing	N	N	N	N	5.8G radar proximity sensing. When someone is recognized at a distance of about 1m, the indicator light of the button is lit actively.	5.8G radar proximity sensing. When someone is recognized at a distance of about 1m, the indicator light of the button is lit actively.	5.8G radar proximity sensing. When someone is recognized at a distance of about 1m, the indicator light of the button is lit actively.	5.8G radar proximity sensing. When someone is recognized at a distance of about 1m, the indicator light of the button is lit actively.